

ABT-EKB-20M

EN 54-16

MICROPHONE KEYBOARD EXTENSION

- ✓ Can be attached to a fireman microphone or a zone microphone
- ✓ Offers an additional 20 function buttons


CNBOP-PIB
3959/2020
2909/2017

1488-CPR-0500/W
1438-CPR-0527


Each extension that is connected to a fireman's or zone microphone provides an additional 20 freely programmable function buttons. In accordance with EN54-16, one of

the buttons can trigger a test of the microphone's optical and acoustic signalling.

	ABT-EKB-20M
Power supply	RJ45 from DFMS or DMS
Degree of protection	IP 31
Keyboard and controls	
Number of keys	20
Additional three normative controls	20x RGB + 20x green
LED colors	RGB (red, green, blue) + separate LED green
Other parameters	
Operating temperature	0°C to 60°C
Operating humidity	15% to 80%
Storage temperature	-20°C to 70°C
Storage humidity	5% to 95%
Dimensions	120 (W) x 55 (H) x 210 (D) mm
Weight	1,4 kg
Space for description at the buttons on the left, dimensions	120 (W) x 55 (H) x 210 (D) mm